

Printerkabel

Printer kabel layout voor Holborn 6100 / 6500
Printer cable for Holborn 6100 / 6500

| 36 pin centronics | 25 pin sub-D male |
|-------------------|-------------------|
| 1 | 9 |
| 2 | 1 |
| 3 | 2 |
| 4 | 3 |
| 5 | 4 |
| 6 | 5 |
| 7 | 6 |
| 8 | 7 |
| 9 | 8 |
| 10 | 11 |
| 11 | 23 |
| 12 | 13 |
| 13 | 24 |
| 14 | |
| 15 | |
| 16 | 22 |
| 17 | 22 |
| 18 | |
| 19 | 22 |
| 20 | |
| 21 | 15 |
| 22 | 16 |
| 23 | |
| 24 | |
| 25 | 19 |
| 26 | 20 |
| 27 | |
| 28 | |
| 29 | |
| 30 | 22 |
| 31 | 10 |
| 32 | 12 |
| 33 | |
| 34 | |
| 35 | |
| 36 | |

Roland Huisman, 11-8-2013
Technischmuseum.nl